

ELECTRONIC COMPONENT PACKAGING SOLUTIONS

ERSACOUN

Universal Parts Counter

MANUAL EQUIPMENT

AUTOMATIC EQUIPMENT

VISION

MARKING

AUTOMATED SOLUTIONS

COMPONENT PROCESSING

The VERSACOUNT II+ can operate with surface mount devices. as well as axial and radial taped components with the optional module.

V-TEK's VERSACOUNT II+ can be programmed to count a specific number of parts. With the optional Empty Pocket Detector, it will detect empty pockets and display the actual number of parts along with the number of empty pockets (EPD optional).

No parts counter is right for the job if it is not accurate. The VERSACOUNT II+ is designed to provide a 100% accurate count whether going forward or backward.



* *	
W	
H	ŀ
K	
-	ľ
H	
100	ŀ
F	

- Bidirectional counting from 2 mm pitch up to 104 mm pitch
- User friendly operator interface
- Works with standard carrier tape widths from 8 mm to 120 mm
- Accepts 7 and 13 inch reels
- Can be programmed to count a specific number of parts
- Interface can display all standard and optional measurements
- Dimensions: height 13" (33 cm) width 36" (92 cm) depth 11.50" (29 cm)
- Power required: 120/230 VAC, 50/60 Hz Weight: 26.00lbs (12.00 Kg)

- Riser for 22" diameter reel
- EPD
- Axial/Radial module
- Thermal Label Printer with barcode
- PC Software Communications



V-TEK, Incorporated 751 Summit Avenue Mankato, MN 56001 (P) 507 387 2039

(F) 507 387 2257

Although the information, recommendations and images on this technical sheet are believed to be correct, V-TEK, Inc. makes no representations or warranties as to the completeness or accuracy of the information and images. Please contact your V-TEK representative for the most current technical specifications and design developments.

WI201.21 REV. 3

05/13/14 PAGE 1 OF 1

www.vtekusa.com